

A100M

Wideband Monaural Headset



Features

- Superior wideband sound thanks to optimised speaker tuning
- 300° flexible boom
- Passive noise cancelling microphone
- Quick Release (QR) adapters for different connectors



The Snom A100M is a wired monaural headset designed for maximum comfort and performance. Its lightweight and ergonomic design means it can be worn comfortably all day.

The wideband technology ensures high-definition sound and crystal-clear communication.

In addition the flexible boom and the passive noise cancelling microphone guarantee clear voice transmission.

With the various Quick Release (QR) adapters available this headset is perfect for use in multiple scenarios.

A100M

Wideband Monaural Headset

Design

- Durable, lightweight steel-reinforced headband
- Leatherette ear cushions
- Ultra lightweight: 56 g (excluding cable)
- 1 m cable with clip

Speaker

- Impedance: 150 Ohm \pm 15 Ohm, ETSI wideband
- Frequency range: 150 – 6,800 Hz
- Max. noise level: 99 dB \pm 3dB

Microphone

- Frequency range: 100 - 10,000 Hz
- Noise canceling: Passive
- Sensitivity: -35 dB \pm 3 dB Standard (E-STD)
- Boom: bendable, pivotable through 300°

Package contents

- Wideband Monaural Headset
- Quick Release (QR) cable with 4P4C connector, 60 cm (extended 2.4m)
- Ear cushion replacement

Marking

- CE
- FCC

Part Number: 00004341

Product numbers for optional accessories

- 00004343 ACUSB adapter cable for USB devices
- 00004344 ACPJ adapter cable for 3.5 mm jacks
- 00004371 ACPJ25 adapter cable for 2.5mm jacks

Compatible landline telephones

- Snom D120
- Snom D3xx series
- Snom D7xx series
- Snom M series (with ACPJ adapter)
- Snom M-SC series (with ACPJ25 adapter)